

**D40ES**



## **Everywhere, Any time with your D40ES!**

Break through the time & space limitations!

People travel from time to time!

You can't be at your partner's award presentation in New York because you had a Sales meeting in Shanghai the other day! Clevo's **D40ES**

combine the powerful Pentium 4 CPU, 15" TFT LCD, Video Camera,

and popular communications like Bluetooth, Wireless LAN, and Ethernet .

Your partner will be able to feel your cares at all times!



**CLEVO**<sup>®</sup>

# D40ES Specification



**CLEVO**<sup>®</sup>

Model	D40ES
CPU	<ul style="list-style-type: none"> <li>Intel<sup>®</sup> Pentium<sup>®</sup> 4 Processor 2.26/2.40/2.53/2.66/2.80GHz (130nm, FSB533, 512 KB L2 cache, mPGA478)</li> <li>Intel<sup>®</sup> Celeron<sup>®</sup> D Processor 2.00/2.20/2.40/2.60/2.80GHz (130nm, FSB533, 128 KB L2 cache, mPGA478)</li> <li>Intel<sup>®</sup> Celeron<sup>®</sup> D Processor 320/325/330/335(2.40~2.80GHz, 90nm, FSB533, 256 KB L2 cache, mPGA478)</li> </ul>
Core Logic	<ul style="list-style-type: none"> <li>SIS M650 + 962</li> </ul>
Display	<ul style="list-style-type: none"> <li>14.1" XGA TFT (1024x768) / 15.0" XGA TFT (1024x768) / 15.0" SXGA+ TFT (1400x1050)</li> </ul>
Memory	<ul style="list-style-type: none"> <li>64-bit wide DDR data channel</li> <li>Two 200-pin SODIMM sockets, supporting DDR266/333</li> <li>Expandable Memory up to 1024MB, based on 128/256/512MB SODIMM Module</li> </ul>
Video Controller	<ul style="list-style-type: none"> <li>SIS M650 integration</li> <li>Shared Memory Architecture with 16/32/64MB</li> <li>128 bit graphic engine</li> <li>Ultra AGP 4X</li> <li>Fully DirectX 8.1 support</li> </ul>
Storage	<ul style="list-style-type: none"> <li>One Fixed 3.5" FDD</li> <li>One changeable 2.5" 9.5/12.7mm(H) HDD Drive</li> <li>One changeable 12.7mm(H) CD-ROM / DVD-ROM / Combo / DVD-Dual Drive</li> <li>Supporting Master IDE mode ATA- 33/66/100/133 (Ultra DMA)</li> </ul>
Keyboard	<ul style="list-style-type: none"> <li>A4 size keyboard, Multi-Language support</li> <li>Built-in Touchpad with scrolling function</li> </ul>
Sound System	<ul style="list-style-type: none"> <li>AC'97 2.2 Compliant Interface</li> <li>3D stereo enhanced sound system</li> <li>Sound-Blaster PRO<sup>™</sup> compatible</li> <li>S/PDIF Digital output (5.1 CH)</li> <li>1x Built-in Microphone</li> <li>2x Built-in Speakers</li> </ul>
I/O Ports	<ul style="list-style-type: none"> <li>3x USB 2.0 ports</li> <li>1x Mini IEEE1394a port</li> <li>1x S-Video jack for TV output</li> <li>1x Serial port</li> <li>1x Parallel port (LPT1), supporting ECP/EPP</li> <li>1x Infrared File Transfer port</li> <li>1x External CRT monitor port</li> <li>1x PS/2 port</li> <li>1x Headphone jack</li> <li>1x Microphone jack</li> <li>1x S/PDIF jack</li> <li>1x RJ-45 port for LAN</li> <li>1x RJ-11 port for Modem</li> <li>1x DC-In jack</li> </ul>
PCMCIA	<ul style="list-style-type: none"> <li>1x Type II PCMCIA socket</li> </ul>
Communication	<ul style="list-style-type: none"> <li>Infrared File Transfer : 115.2Kbps SIR/4Mbps FIR, IrDA 1.1 compliant</li> <li>10/100BASE-TX Fast Ethernet on board</li> <li>Integrated V.90/56K MDC Modem (V.92 compliant)</li> <li>(Option) 802.11b Wireless LAN module, USB interface</li> <li>(Option) Bluetooth 1.1 Module, USB interface</li> <li>(Factory option) 300K-pixel Video Camera module</li> </ul>
Power	<ul style="list-style-type: none"> <li>Full Range 100W AC adapter - AC input 100~240V, 50~60Hz, DC output 20V, 6A</li> <li>Changeable 8-cell Smart Li-ion battery pack, 4400mAh</li> </ul>
Security	<ul style="list-style-type: none"> <li>Kensington<sup>®</sup> Lock</li> </ul>
Dimension	<ul style="list-style-type: none"> <li>329(W) x 275(D) x 36.5(H)mm, 13.0"(W) x 10.8"(D) x 1.4"(H)</li> <li>3.1Kg with 8 cells Lithium-ion battery</li> </ul>
Options	<ul style="list-style-type: none"> <li>One changeable 12.7mm(H) CD-ROM / DVD-ROM / Combo / DVD-Dual Drive</li> <li>Software DVD Player</li> <li>802.11b Wireless LAN module, USB interface</li> <li>Bluetooth 1.1 Module, USB interface</li> <li>(Factory option) 300K-pixel Video Camera module</li> </ul>

2004/09 Version